



1. Secure the Extension Mount Bracket to the Yagi Antenna with two 1/4" Screws fastened into two 1/4" Lock Washers and 1/4" Hex Nuts.
2. Attach the assembly to the Base Mount Bracket with two 1/4" Screws fastened into two 1/4" Lock Washers and 1/4" Hex Nuts.
3. Mount the Yagi Antenna assembly to the tower by feeding two Hose Clamps through the slots of the Base Mount Bracket and tightening them down until the antenna is secure.
4. Please Note:
 - Yagi Antennas amplify 800MHz-900MHz frequencies for GSM and CDMA cellular providers. If the provider uses other frequencies, the antenna will not be effective.
 - Yagi Antennas are directional and must be pointed towards the nearest tower. Keep the hose clamps loose until you find the peak signal.